

**T90H-WW IP:**

**DMX channel's functions and their values (316/8 DMX channels):**

Model/Channel			Value	Function	Default Dmx	Time/Speed	
3CH	6CH	8CH					
NA	1	1	0-31	<b>Shutter, strobe:</b>	32	1-25HZ	关闭
			32-63	Led turn off			
			64-95	Led turn on			
			96-127	Strobe effect slow to fast			
			128-159	Led turn on			
			160-191	Pulse-effect in sequences			
			192-223	Led turn on			
1	2	2	224-255	Random strobe effect slow to fast	0	1-25HZ	打开光
				Led turn on			
NA	NA	3	0-255	<b>Dimmer intensity:</b>	0		同步频闪从慢到快
				Intensity 0 to 100%			
NA	3	4	0-255	<b>Fine Dimmer intensity:</b>	0		打开光
				Dimmer intensity fine			
			0-20	<b>Dim Curves:</b>			
			21-40	Standard			
			41-60	Stage			
			61-80	TV			
			81-100	Architectural			
2	4	5	101-255	Theatre	0	25.16RPM-0.57RPM	脉冲同步频闪
				Default to Unit Curve Setting			
			0-127	<b>Rotating gobo index</b>			
			128-189	Gobo indexing (0-360°)			
3	5	6	190-193	Clockwise gobo scroll from fast to slow	0	0.57RPM-25.16RPM	图案旋转定位
			194-255	No rotation			
				Counter-clockwise gobo scroll from slow to fast			
			0-79	<b>Special Control:</b>			
			80-84	Normal			
			85-87	Reset All			
			88-90	No function			
			91-93	No function			
			94-96	No function			
			97-99	No function			
			100-119	Internal program 1(secne1~8 of EEPROM)			
			120-139	Internal program 2(secne9~16 of EEPROM)			
			140-159	Internal program 3(secne17~24 of EEPROM)			
			160-179	Internal program 4(secne25~32 of EEPROM)			
			180-199	Internal program 5(secne33~40 of EEPROM)			
			200-219	Internal program 6(secne41~48 of EEPROM)			
			220-239	Internal program 7(secne49~56 of EEPROM)			
			240-255	No function			
NA	6	7	0-255	<b>Warm White LED 1 :</b>	255		正常状态
				Warm White ( 0-Black , 255-100% White )			
NA	NA	8	0-255	<b>Warm White LED Fine 1.:</b>	0		等待8秒后所有电机重设
				Fine control for Warm White adjustment			

批准: 审核: 校对: 制定: 张镇邦