

## OVAL60D :

### DMX channel's functions and their values :

Mode/Channel				Value	Function
5CH	6CH	8CH	10CH		
1	1	1	1	0-255	<b>Red LED :</b> Red ( 0-Black , 255-100% Red ) LED红色从0~100%
2	2	2	2	0-255	<b>Green LED :</b> Green ( 0-Black , 255-100% Green ) LED绿色从0~100%
3	3	3	3	0-255	<b>Blue LED :</b> Blue ( 0-Black , 255-100% Blue ) LED蓝色从0~100%
4	4	4	4	0-255	<b>White LED :</b> White ( 0-Black , 255-100% White ) LED白色从0~100%
5	5	5	5	0-255	<b>Amber LED :</b> Amber ( 0-Black , 255-100% Amber ) LED琥珀色从0~100%
NA	NA	6	6	0 1-255	<b>Color Temperature:</b> No function Color Temperature(2700K-7200K) 色温从2700K到7200K
NA	NA	7	7	0 1-7 8-15 16-23 24-31 32-39 40-47 48-55 56-63 64-71 72-79 80-87 88-95 96-103 104-111 112-119 120-127 128-135 136-143 144-151 152-159 160-167 168-175 176-183 184-191 192-199 200-207 208-215 216-223 224-231	<b>Color macros:</b> No function 混色效果1 混色效果2 混色效果3 混色效果4 混色效果5 混色效果6 混色效果7 混色效果8 混色效果9 混色效果10 混色效果11 混色效果12 混色效果13 混色效果14 混色效果15 混色效果16 混色效果17 混色效果18 混色效果19 混色效果20 混色效果21 混色效果22 混色效果23 混色效果24 混色效果25 混色效果26 混色效果27 混色效果28 混色效果29

				232-239	Color Macro 30	混色效果30
				240-247	Color Macro 31	混色效果31
				248-255	Color Macro 32	混色效果32
NA	NA	NA	8		<b><u>internal programs:</u></b> 0-10 without internal program 11-40 internal program 1 41-70 internal program 2 71-100 internal program 3 101-130 internal program 4 131-160 internal program 5 161-190 internal program 6 191-220 internal program 7 221-255 gradient effect	无内置程序 内置程序1 内置程序2 内置程序3 内置程序4 内置程序5 内置程序6 内置程序7 渐变效果
NA	NA	NA	9		<b><u>Shutter, strobe:</u></b> 0-31 Led trun off 32-63 Led turn on 64-95 Strobe effect slow to fast 96-127 Led turn on 128-159 Pulse-effect in sequences 160-191 Led turn on 192-223 Random strobe effect slow to fast 224-255 Led turn on	关闭 打开光 同步频闪从慢到快 打开光 脉冲同步频闪 打开光 异步频闪从慢到快 打开光
NA	6	8	10	0-255	<b><u>General dimming/speed:</u></b> dimming( 0-Black , 255- 100% ) speed from slow to fast /when running internal programs speed from slow to fast /when running gradient effect	总调光从0~100% 内置程序时为速度调节由慢到快 渐变效果时为速度调节由慢到快